Yuasa Technical Data Sheet

Yuasa SWL+2250-12 Industrial VRLA Battery

Specifications	
Nominal voltage (V)	12
10m rate Constant Power (Typ) to 9.6V at 20°C (W/Block)	2250
10m rate Constant Power (Typ) to 1.6V/cell at 20°C (W/Cell)	375
10-hr rate Capacity to 1.75v per cell at 20°C (Ah)	76
10-hr rate Capacity to 1.8V/Cell at 20°C (Ah)	76
20-hr rate Capacity to 1.75V/Cell at 20°C (Ah)	86.0
Dimensions	
Length (mm)	380 (±2)
Width (mm)	166 (±1)
Height (mm)	177.5 (±2)
Mass (kg)	28
Terminal Type	
Threaded terminal - (M=Male or F=Female)	M8 (F)
Torque (Nm)	6
Operating Temperature Range	
Storage (in fully charged condition)	-20°C to +50°C
Charge	-15°C to +50°C
Discharge	-20°C to +60°C
Storage	
Capacity loss per month at 20°C (% approx.)	3
Case Material	
Standard	ABS (UL94:HB)
FR version available	UL94:V0
Charge Voltage	
Float charge voltage at 20°C (V)/Block	13.65 (±1%)
Float charge voltage at 20°C (V)/Cell	2.275 (±1%)
Float Chg voltage tmp correction factor from std 20°C (mV)	-3
Cyclic (or Boost) charge Voltage at 20°C (V)/Block	14.5 (±3%)
Cyclic (or Boost) charge Voltage at 20°C (V)/Cell	2.42 (±3%)
Cyclic Chg voltage tmp correction factor from std 20°C (mV)	-4
Charge Current	
Float charge current limit (A)	No limit
Cyclic (or Boost) charge current limit (A)	19
Maximum Discharge Current	
1 second (A)	800
1 minute (A)	500
Short-Circuit Current & Internal Resistance	
Short-Circuit current - according to EN IEC 60896-21 (A)	1442
Impedance	
Measured at 1 kHz (mΩ)	3.6
Design Life & Approvals	
EUROBAT Classification: Very Long Life	12+ years
Yuasa design life at 20°C (yrs)	up to 15 years



Layout



3rd Party Certifications

ISO9001 - Quality Management Systems
ISO14001 - Environmental Management Systems
ISO45001 OHSAS Management Systems
UNDERWRITERS LABORATORIES Inc.

bsi. ISO 9001 Quality Management
Cert. No.: FM 10626

bsi. ISO 14001 Environmental Management
Cert. No.: EMS 55229

Safety

Installation

Can be installed and operated in orientations up to 90° from the upright position.

Handles

Batteries must not be suspended by their handles (where fitted).

Vent valves

Each cell is fitted with a low pressure release valve to allow gasses to escape and then reseal.

Gas release

VRLA batteries release hydrogen gas which can form explosive mixtures in the air. Do not place inside a sealed container.

Recycling

YUASA's VRLA batteries must be recycled at the end of life in accordance with local and national laws and regulations.

Data Sheet generated on 15/12/2025 – E&OE